

Habotest HT107E Professional Socket Outlet Tester, Phase & Leakage Voltage Frequency, RCD Trip UK Plug



Model: HAHT107EBK
 Manufacture warranty: 12 months
 Country of Origin: China

Features:

- Mini portable design, easy to carry and simple to use.
- RCD (or GFCI) test.
- Phase Voltage, Leakage Voltage & Frequency test (with LCD).
- Can detect the wiring status of the socket quickly and accurately.
- Widely used in the school, laboratory, factory and other social fields.

Description:

- It tests your protection system to ensure the household electrical safety.
- Widely used in the school, laboratory, factory and other social fields.

Specifications:

- Operate voltage: 90 - 250V/45 - 65Hz
- Measure voltage: 90 - 250V/45 - 65Hz
- Leakage voltage: 0 - 99V/45 - 65Hz
- Accuracy: $\pm(2.0\%+2)$
- Altitude: $\leq 2000\text{m}$
- RCD test: $\geq 30\text{mA}$
- RCD working voltage: $220\text{V}\pm 20\text{V}$
- GFCI test: $> 5\text{mA}$
- GFCI working voltage: $110\text{V}\pm 20\text{V}$
- Operating temperature: $0^{\circ}\text{C}\sim 40^{\circ}\text{C}$
- Operating humidity: $20\%\sim 80\%\text{RH}$
- Storage temperature: $-10^{\circ}\text{C}\sim 50^{\circ}\text{C}$
- Storage humidity: $20\%\sim 80\%\text{RH}$
- Safety Rating: EN61010-1,-2-030;EN61326-1,CAT II 300V
- Dimension: 62 x 65 x 58mm
- Weight: 50g



ELECTRICITY NOT TRIP
Power leak-proof protection is not good

ELECTRICITY TRIP
Power leak-proof protection is good

When using, please be careful not to touch the RCD button, so as not to trigger the leakage protection switch, causing unnecessary losses.

Power leak-proof protection switch test

Test result display light

Reference For Test result

Electrically Leak-proof test button

	RED	RED	RED
CORRECT	●	●	●
OPEN GROUND	●	●	●
OPEN NEUTRAL	●	●	●
OPEN LIVE	●	●	●
LIVE/GRD REVERSE	●	●	●
LIVE/NEU REVERSE	●	●	●
LIVE/ GRD REVERSE; missing GRD	●	●	●